



U2000EC202052004



Page: 3

B

Reg No. \_\_\_\_\_

Name: \_\_\_\_\_

**APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY**  
 Fourth Semester B.Tech Degree (S.FE) Examination August 2021 (2015 Scheme)

Course Code: EC202

Course Name: SIGNALS & SYSTEMS

Max. Marks: 100

Duration: 3 Hours

**PART A**

*Answer any two full questions, each carries 15 marks.*

Marks

1 a) Check if the signals below are periodic. If so, find the fundamental period. (6)

(i)  $x(t) = \sin(\sqrt{2}t) + \cos(t)$

(ii)  $x[n] = \sin\left(\frac{2\pi n}{5}\right) + \cos\left(\frac{2\pi n}{3}\right)$

b) Sketch the signal below. (9)

$x(t) = e^{-at}, (a > 0)$

- (i) Represent the signal as a sum of a causal signal and an anti-causal signal.
- (ii) Determine whether it is an energy signal, power signal or neither energy nor power.

2 a) Determine whether the following systems are linear. (10)

(i)  $\frac{d^2}{dt^2} y(t) + 3y(t) = \frac{t^2}{2} x(t)$

(ii)  $y[n] = x^*[n]$ , \* indicating complex conjugate

b) A system is described by the input-output relation described below. Check whether the system is linear and time invariant. (5)

$y[n] = x[kn]$ ,  $k$  a real constant.

3 a) Find the output of the LTI system described by the impulse response (8)

$h[n] = [2, 3, 3, 2]$  to the input signal  $x[n] = [1, 2, 2, 1]$

b) Derive the stability condition of a continuous time LTI system having impulse response  $h(t)$ . (7)

## PART B

Answer any two full questions, each carries 15 marks.

- 4 a) Consider the periodic impulse train (8)

$$b_T(t) = \sum_{k=-\infty}^{\infty} \delta(t - kT)$$

Determine its

- (i) complex exponential Fourier series  
(ii) Trigonometric Fourier Series

- b) Given (7)

$$x(t) \xrightarrow{\text{Fourier Transform}} X(\Omega)$$

show that

$$\int_{-\infty}^{\infty} |x(t)|^2 dt = \frac{1}{2\pi} \int_{-\infty}^{\infty} |X(\Omega)|^2 d\Omega$$

- 5 a) Compute the Laplace Transforms of the signals (9)

(i)  $x(t) = e^{-2t} (u(t) - u(t-5))$

(ii)  $x(t) = \delta(3t+5)$

(iii)  $x(t) = e^{-2t} \cos(\Omega_0 t) u(t)$

- b) The o/p  $y(t)$  of a continuous time LTI system is  $y(t) = 2e^{-3t} u(t)$ , when the input  $x(t)$  is a unit step. Find (6)

(i)  $h(t)$ , the impulse response

(ii)  $y(t)$ , when input  $x(t) = e^{-t} u(t)$

- 6 a) State and prove the sampling theorem for Low pass signals. (10)

- b) A signal  $x(t) = 1 + \cos(5\pi t) + 0.5 \cos(10\pi t)$  is ideally sampled. The interval (5)

between the samples is  $T_s$  seconds. Find

(i) Maximum allowable value for  $T_s$ .

(ii) The minimum bandwidth of the ideal reconstruction filter. Plot its frequency response.



## PART C

Answer any two full questions, each carries 20 marks.

- 7 a) A causal discrete-time LTI system is described by (10)  

$$y[n] - 0.75y[n-1] + 0.125y[n-2] = x[n]$$
 where  $x[n]$  and  $y[n]$  are the input and output of the system, respectively.  
 (a) Determine the system function  $H(z)$ .  
 (b) Find the impulse response  $h[n]$  of the system.  
 (c) Find the step response  $s[n]$  of the system.
- b) Show that (10)  
 (i)  $x_1[n] * x_2[n] \xrightarrow{z} X_1(z)X_2(z)$   
 (ii)  $nx[n] \xrightarrow{z} -z \frac{d}{dz} X(z)$
- 8 a) Find the DFT of the following sequences (9)  
 (i)  $x[n] = \cos \frac{\pi}{4} n$   
 (ii)  $x[n] = \cos \frac{\pi}{4} n + \sin \frac{\pi}{3} n$   
 (iii)  $x[n] = \cos^2 \left( \frac{\pi}{8} n \right)$
- b) Explain the relationship between z-Transform and DTFT (6)
- c) State and Prove the Parseval's relationship for DTFT (5)
- 9 a) Find the DTFT of  $x[n] = u[n] - u[n-N]$  (8)
- b) (i) Find the impulse response of an Ideal Discrete Low Pass filter (LPF) with a (12)  
 cut off frequency  $\omega_c$ .  
 (ii) Is an Ideal LPF realizable in the time domain? Give reasons.

